



Cisco Catalyst 2960-X Series Switches

Ready to Replace an Old Switch?

Newer Catalyst 2960-X Series Switches offer more intelligent features and higher performance at a similar price versus previous models. [Compare now](#)

If you need to support BYOD and mobility, consider Catalyst 3650 Series Switches. [Compare](#) with 2960-X Series Switches

- [Get trade-in discounts](#) when you buy new switches.
-
-

Cisco Catalyst 2960-X Series Switches

Cisco® Catalyst® 2960-X Series Switches are fixed-configuration, stackable Gigabit Ethernet switches that provide enterprise-class access for campus and branch applications (Figure 1). Designed for operational simplicity to lower total cost of ownership, they enable scalable, secure and energy-efficient business operations with intelligent services and a range of advanced Cisco IOS® Software features.

Figure 1. A Cisco Catalyst 2960-X Series Switch Family



Product Highlights

Cisco Catalyst 2960-X switches feature:

- 24 or 48 Gigabit Ethernet ports with line-rate forwarding performance
- Gigabit Small Form-Factor Pluggable (SFP) or 10G SFP+ uplinks
- FlexStack Plus for stacking of up to 8 switches with 80 Gbps of stack throughput (optional)
- Power over Ethernet Plus (PoE+) support with up to 740W of PoE budget
- Reduced power consumption and advanced energy management features
- USB and Ethernet management interfaces for simplified operations
- Application visibility and capacity planning with integrated NetFlow-Lite
- LAN Base or LAN Lite Cisco IOS® software features
- Enhanced limited lifetime warranty (E-LLW) offering next-business-day hardware replacement

Cisco Catalyst 2960-XR models also offer:

- Power resiliency with optional dual field-replaceable power supplies
- IP Lite Cisco IOS® software with dynamic routing and Layer 3 features

Switch Models and Configurations

Catalyst 2960-X switches include a single fixed power supply and are available with either the Cisco IOS LAN Base or LAN Lite feature set. Catalyst 2960-XR switch models include a field-replaceable modular power supply and can accommodate a second power supply. Catalyst 2960-XR is available only with the Cisco IOS IP Lite feature set.

Table 1. Cisco Catalyst 2960-X Configurations

| Model | 10/100/1000 Ethernet Ports | Uplink Interfaces | Cisco IOS Software Image | Available PoE Power | FlexStack-Plus Capability |
|------------------------------|----------------------------|-------------------|--------------------------|---------------------|---------------------------|
| Cisco Catalyst 2960X-48FPD-L | 48 | 2 SFP+ | LAN Base | 740W | Y |
| Cisco Catalyst 2960X-48LPD-L | 48 | 2 SFP+ | LAN Base | 370W | Y |
| Cisco Catalyst 2960X-24PD-L | 24 | 2 SFP+ | LAN Base | 370W | Y |

| Model | 10/100/1000 Ethernet Ports | Uplink Interfaces | Cisco IOS Software Image | Available PoE Power | FlexStack-Plus Capability |
|------------------------------|----------------------------|---------------------------|--------------------------|---------------------|---------------------------|
| Cisco Catalyst 2960X-48TD-L | 48 | 2 SFP+ | LAN Base | - | Y |
| Cisco Catalyst 2960X-24TD-L | 24 | 2 SFP+ | LAN Base | - | Y |
| Cisco Catalyst 2960X-48FPS-L | 48 | 4 SFP | LAN Base | 740W | Y |
| Cisco Catalyst 2960X-48LPS-L | 48 | 4 SFP | LAN Base | 370W | Y |
| Cisco Catalyst 2960X-24PS-L | 24 | 4 SFP | LAN Base | 370W | Y |
| Cisco Catalyst 2960X-24PSQ-L | 24 (8PoE) | 2 SFP, 2 10/100/1000BT | LAN Base | 110W | - |
| Cisco Catalyst 2960X-48TS-L | 48 | 4 SFP | LAN Base | - | Y |
| Cisco Catalyst 2960X-24TS-L | 24 | 4 SFP | LAN Base | - | Y |
| Cisco Catalyst 2960X-48TS-LL | 48 | 2 SFP | LAN Lite | - | - |
| Cisco Catalyst 2960X-24TS-LL | 24 | 2 SFP | LAN Lite | - | - |

Table 2. Cisco Catalyst 2960-XR Configurations

| Model | 10/100/1000 Ethernet Ports | Uplink Interfaces | Cisco IOS Software Image | Available PoE Power | Power Supply |
|-------------------------------|----------------------------|-------------------|--------------------------|---------------------|--------------|
| Cisco Catalyst 2960XR-48FPD-I | 48 | 2 SFP+ | IP Lite | 740W | 1025WAC |
| Cisco Catalyst 2960XR-48LPD-I | 48 | 2 SFP+ | IP Lite | 370W | 640WAC |
| Cisco Catalyst 2960XR-24PD-I | 24 | 2 SFP+ | IP Lite | 370W | 640WAC |
| Cisco Catalyst 2960XR-48TD-I | 48 | 2 SFP+ | IP Lite | - | 250WAC |
| Cisco Catalyst 2960XR-24TD-I | 24 | 2 SFP+ | IP Lite | - | 250WAC |
| Cisco Catalyst 2960XR-48FPS-I | 48 | 4 SFP | IP Lite | 740W | 1025WAC |
| Cisco Catalyst 2960XR-48LPS-I | 48 | 4 SFP | IP Lite | 370W | 640WAC |
| Cisco Catalyst 2960XR-24PS-I | 24 | 4 SFP | IP Lite | 370W | 640WAC |
| Cisco Catalyst 2960XR-48TS-I | 48 | 4 SFP | IP Lite | - | 250WAC |
| Cisco Catalyst 2960XR-24TS-I | 24 | 4 SFP | IP Lite | - | 250WAC |

Catalyst 2960-X series Software Features

All Catalyst 2960-X Series Switches use a single Universal Cisco IOS Software Image for all SKUs. Depending on the switch model, the Cisco IOS image automatically configures either the LAN Lite, LAN Base, or IP Lite feature set.

LAN Lite models have reduced functionality and scalability for small deployments with basic requirements. Cisco Catalyst 2960-X Family of Switches are available with the LAN Base and LAN Lite feature sets and Catalyst 2960-XR Family of switches are available IP Lite feature sets.

Note that each switch model is tied to a specific feature level; LAN Lite cannot be upgraded to LAN Base and LAN Base cannot be upgraded to IP Lite.

For more information about the features included in the LAN Lite, LAN Base and IP Lite feature sets, refer to Cisco Feature Navigator: <http://tools.cisco.com/ITDIT/CFN/jsp/index.jsp>.

Cisco Catalyst 2960-XR IP-Lite High-Performance Routing

The Cisco hardware routing architecture delivers extremely high-performance IP routing in the Cisco Catalyst 2960-XR IP-Lite Switches:

- **IP unicast routing protocols (Static, Routing Information Protocol Version 1 [RIPv1], and RIPv2, RIPv6, and RIPv6 Next Generation [RIPv6ng])** are supported for small-network routing applications.
- **Advanced IP unicast routing protocols (OSPF for Routed Access)** are supported for load balancing and constructing scalable LANs. IPv6 routing (OSPFv3) is supported in hardware for maximum performance.
- **Equal-cost routing** facilitates Layer 3 load balancing and redundancy across the stack.
- **Policy-based routing (PBR)** allows superior control by facilitating flow redirection regardless of the routing protocol configured.
- **Hot Standby Routing Protocol (HSRP) and Virtual Router Redundancy Protocol (VRRP)** provides dynamic load balancing and failover for routed links.
- **Protocol Independent Multicast (PIM)** for IP multicast is supported, including PIM sparse mode (PIM-SM), PIM dense mode (PIM-DM), PIM sparse-dense mode and Source Specific Multicast (SSM).

Network Security

The Cisco Catalyst 2960-X Series Switches provide a range of security features to limit access to the network and mitigate threats, including:

- **Cisco TrustSec uses SXP** to simplify security and policy enforcement throughout the network. For more information about Cisco TrustSec security solutions, visit cisco.com/go/TrustSec.
- **Comprehensive 802.1X** Features to control access to the network, including Flexible Authentication, 802.1x Monitor Mode, and RADIUS Change of Authorization.
- **IPv6 First-Hop Security** enhances Layer-2 and Layer-3 network access from proliferating IPv6 devices especially BYOD devices. It protects against rogue router advertisements, address spoofing, fake DHCP replies and other risks introduced by IPv6 technology.
- **Device Sensor and Device Classifier** enable seamless versatile device profiles including BYOD devices. They also enable Cisco Identity Services Engine (ISE) to provision identity based security policies (ISE is supported in 2960-XR SKUs only).
- **Cisco Trust Anchor Technology (TAT)** enables easy distribution of a single universal image for all models of Catalyst 2960-X by verifying the authenticity of IOS images. This technology allows the switch to perform IOS integrity checks at boot-up by verifying the signature, verifying the Trusted Asset under Management (TAM) and authenticating the license.
- **Cisco Threat Defense** features including Port Security, Dynamic ARP Inspection, and IP Source Guard.
- **Private VLANs** restrict traffic between hosts in a common segment by segregating traffic at Layer 2, turning a broadcast segment into a nonbroadcast multi access like segment. This feature is available in IP-Lite feature set only.
 - **Private VLAN Edge** provides security and isolation between switch ports, which helps ensure that users cannot snoop on other users' traffic.
- **Unicast Reverse Path Forwarding (RPF)** feature helps mitigate problems caused by the introduction of malformed or forged (spoofed) IP source addresses into a network by discarding IP packets that lack a verifiable IP source address. This feature is available in IP-Lite feature set only.
- **Multidomain Authentication** allows an IP phone and a PC to authenticate on the same switch port while placing them on appropriate voice and data VLAN.
- **Access Control Lists** for Pv6 and IPv4 for security and QoS ACEs.

- **VLAN ACLs** on all VLANs prevent unauthorized data flows from being bridged within VLANs.
- **Router ACLs** define security policies on routed interfaces for control-plane and data-plane traffic. IPv6 ACLs can be applied to filter IPv6 traffic.
- **Port-based ACLs** for Layer 2 interfaces allow security policies to be applied on individual switch ports.
- **Secure Shell (SSH) Protocol, Kerberos, and Simple Network Management Protocol Version 3 (SNMPv3)** provide network security by encrypting administrator traffic during Telnet and SNMP sessions. SSH Protocol, Kerberos, and the cryptographic version of SNMPv3 require a special cryptographic software image because of U.S. export restrictions.
- **Switched Port Analyzer (SPAN)**, with bidirectional data support, allows Cisco Intrusion Detection System (IDS) to take action when an intruder is detected.
- **TACACS+ and RADIUS authentication** facilitates centralized control of the switch and restricts unauthorized users from altering the configuration.
- **MAC Address Notification** allows administrators to be notified of users added to or removed from the network.
- **Multilevel security on console access** prevents unauthorized users from altering the switch configuration.
- **Bridge protocol data unit (BPDU) Guard** shuts down Spanning Tree Port Fast-enabled interfaces when BPDUs are received to avoid accidental topology loops.
- **Spanning Tree Root Guard (STRG)** prevents edge devices not in the network administrator's control from becoming Spanning Tree Protocol root nodes.
- **IGMP filtering** provides multicast authentication by filtering out nonsubscribers and limits the number of concurrent multicast streams available per port.
- **Dynamic VLAN assignment** is supported through implementation of VLAN Membership Policy Server client capability to provide flexibility in assigning ports to VLANs. Dynamic VLAN facilitates the fast assignment of IP addresses.

Redundancy and Resiliency

Cisco Catalyst 2960-X Series Switches offer a number of redundancy and resiliency features to prevent outages and help ensure that the network remains available:

- **Cross-stack EtherChannel** provides the ability to configure Cisco EtherChannel technology across different members of the stack for high resiliency.
- **Flexlink** provides link redundancy with convergence time less than 100 milliseconds.
- **IEEE 802.1s/w Rapid Spanning Tree Protocol (RSTP) and Multiple Spanning Tree Protocol (MSTP)** provide rapid spanning-tree convergence independent of spanning-tree timers and also offer the benefit of Layer 2 load balancing and distributed processing. Stacked units behave as a single spanning-tree node.
- **Per-VLAN Rapid Spanning Tree (PVRST+)** allows rapid spanning-tree reconvergence on a per-VLAN spanning-tree basis, without requiring the implementation of spanning-tree instances.
- **Cisco Hot Standby Router Protocol (HSRP)** is supported to create redundant, fail safe routing topologies in 2960-XR IP-Lite SKUs.
- **Switch-port auto-recovery (Error Disable)** automatically attempts to reactivate a link that is disabled because of a network error.

- **Power redundancy** with an optional second power supply on 2960-XR models, or with an external RPS on 2960-X models.

Enhanced Quality of Service

The Cisco Catalyst 2960-X Series Switches offers intelligent traffic management that keeps everything flowing smoothly. Flexible mechanisms for marking, classification, and scheduling deliver superior performance for data, voice, and video traffic, all at wire speed. Primary QoS features include:

- Up to **eight egress queues** per port (four on the 2960-X or when stacking the 2960-XR) and strict priority queuing so that the highest priority packets are serviced ahead of all other traffic.
- **Shaped Round Robin (SRR)** scheduling and **Weighted Tail Drop (WTD)** congestion avoidance.
- **Flow-based rate limiting** and up to 256 aggregate or individual policers per port.
- **802.1p class of service (CoS)** and **Differentiated Services Code Point (DSCP)** classification, with marking and reclassification on a per-packet basis by source and destination IP address, MAC address, or Layer 4 TCP/UDP port number.
- **Cross-stack QoS** to allow QoS to be configured across a stack of 2960-X series switches.
- **The Cisco committed information rate (CIR)** function provides bandwidth in increments as low as 8 Kbps.
- **Rate limiting** is provided based on source and destination IP address, source and destination MAC address, Layer 4 TCP/UDP information, or any combination of these fields, using QoS ACLs (IP ACLs or MAC ACLs), class maps, and policy maps.

Cisco FlexStack-Plus

Cisco FlexStack-Plus provides stacking of up to eight 2960-X switches with the optional FlexStack-Plus module ([Figure 2](#)).

The FlexStack-Plus module is hot swappable and can be added to any Cisco Catalyst 2960-X or Catalyst 2960-XR with a FlexStack-Plus slot. Switches connected to a stack will automatically upgrade to the stack's Cisco IOS Software version and transparently join the stack without additional intervention.

Cisco FlexStack-Plus and Cisco IOS Software offer true stacking, with all switches in a stack acting as a single switch unit. FlexStack-Plus provides a unified data plane, unified configuration, and single IP address for switch management. The advantages of true stacking include lower total cost of ownership and higher availability through simplified management as well as cross-stack features including EtherChannel, SPAN, and FlexLink.

To provide investment protection, FlexStack-Plus is backwards-compatible with FlexStack. Cisco Catalyst 2960-X LAN Base switches equipped with a FlexStack-Plus module can be stacked with Catalyst 2960-S and 2960-SF LAN Base switches equipped with a FlexStack module (see [Table 5](#)).

Table 3. FlexStack and FlexStack Plus Supported Combinations

| | 2960-XR IP Lite | 2960-X LAN Base | 2960-S/SF LAN Base |
|-----------------------------------|-----------------|-----------------|--------------------|
| 2960-XR IP Lite | Yes | - | - |
| 2960-X LAN Base | - | Yes | Yes |
| 2960-S or 2960-SF LAN Base | - | Yes | Yes |

Table 4. FlexStack-Plus Scalability and Performance

| Stack Members | Stack Bandwidth | Stack Limit | Cisco IOS Feature Set |
|---|-----------------|-------------|-----------------------|
| 2960-XR IP Lite | 80G | 8 | IOS IP Lite |
| 2960-XLAN Base | 80G | 8 | IOS LAN Base |
| 2960-X LAN Base mixed with 2960-S/SF LAN Base | 40G | 4 | IOS LAN Base |

Figure 2. Cisco FlexStack-Plus Switch Stack



Power Supply

The Catalyst 2960-X switches comes with one fixed power-supply and options for an external redundant power supply source (RPS2300).

The Catalyst 2960-XR switches support dual redundant power supplies. The Catalyst 2960-XR ships with one power supply by default. The second power supply can be purchased at the time of ordering the switch or as a spare. These power supplies have in-built fans to provide cooling.

Figure 3. 2960-XR Family Power Supply



The following table shows the different power supplies available in these switches and the available PoE power.

Table 5. 2960-XR Default Power Supply Configurations

| Models | Default Power Supply | Available PoE Power |
|--|----------------------|---------------------|
| WS-C2960XR-24TS-I WS-C2960XR-48TS-I WS-C2960XR-24TD-I WS-C2960XR-48TD-I | PWR-C2-250WAC | - |
| WS-C2960XR-24PD-I WS-C2960XR-48LPD-I WS-C2960XR-24PS-I WS-C2960XR-48LPS-I | PWR-C2-640WAC | 370W |
| WS-C2960XR-48FPD-I WS-C2960XR-48FPS-I | PWR-C2-1025WAC | 740W |

Intelligent Power over Ethernet Plus

Cisco Catalyst 2960-Xseries switches support both IEEE 802.3af Power over Ethernet (PoE) and IEEE 802.3at PoE+ (up to 30W per port) to deliver lower total cost of ownership for deployments that incorporate Cisco IP phones, Cisco Aironet® wireless access points, or other standards-compliant PoE/PoE+ end devices. PoE removes the need to supply wall power to PoE-enabled devices and eliminates the cost of adding electrical cabling and circuits that would otherwise be necessary in IP phone and WLAN deployments.

The Catalyst 2960-X series PoE power allocation is dynamic and power mapping scale up to a maximum of 740W PoE+ power.

The 2960-XR switch configurations offer the additional benefit of dual redundant power supplies. If both power supplies are used, then the 2960-XR shares the load between the two power supplies for non stop power.

Table 6. 2960-X PoE and PoE+ Power Capacity

| Switch Model | Maximum Number of PoE+ (IEEE 802.3at) Ports* | Maximum Number of PoE (IEEE 802.3af) Ports* | Available PoE Power (Single PS Source) |
|-------------------------------|--|---|--|
| Cisco Catalyst 2960X-48FPD-L | 24 ports up to 30W | 48 ports up to 15.4W | 740W |
| Cisco Catalyst 2960X-48LPD-L | 12 ports up to 30W | 24 ports up to 15.4W | 370W |
| Cisco Catalyst 2960X-24PD-L | 12 ports up to 30W | 24 ports up to 15.4W | 370W |
| Cisco Catalyst 2960X-48FPS-L | 24 ports up to 30W | 48 ports up to 15.4W | 740W |
| Cisco Catalyst 2960X-48LPS-L | 12 ports up to 30W | 24 ports up to 15.4W | 370W |
| Cisco Catalyst 2960X-24PS-L | 12 ports up to 30W | 24 ports up to 15.4W | 370W |
| Cisco Catalyst 2960X-24PSQ-L | 3 ports up to 30W | 7 ports up to 15.4W | 110W |
| Cisco Catalyst 2960XR-48FPD-I | 24 ports up to 30W | 48 ports up to 15.4W | 740W |
| Cisco Catalyst 2960XR-48LPD-I | 12 ports up to 30W | 24 ports up to 15.4W | 370W |
| Cisco Catalyst 2960XR-24PD-I | 12 ports up to 30W | 24 ports up to 15.4W | 370W |
| Cisco Catalyst 2960XR-48FPS-I | 24 ports up to 30W | 48 ports up to 15.4W | 740W |
| Cisco Catalyst 2960XR-48LPS-I | 12 ports up to 30W | 24 ports up to 15.4W | 370W |
| Cisco Catalyst 2960XR-24PS-I | 12 ports up to 30W | 24 ports up to 15.4W | 370W |

* Intelligent power management allows flexible power allocation across all ports.

Table 7. 2960-XR Available PoE and Switch Power Capabilities with Different Combinations of Power Supplies

| Primary Power Supply | Secondary Power Supply | Available Power for PoE+ | Switch Power Redundancy | Available PoE Power When One PS fails |
|----------------------|------------------------|--------------------------|-------------------------|---------------------------------------|
| PWR-C2-250WAC | - | - | No | - |
| PWR-C2-250WAC | PWR-C2-250WAC | - | Yes | - |
| PWR-C2-640WAC | - | 370W | No | - |
| PWR-C2-640WAC | PWR-C2-640WAC | 370W | Yes | 370W |
| PWR-C2-1025WAC | - | 740W | No | - |
| PWR-C2-1025WAC | PWR-C2-1025WAC | 740W | Yes | 740W |

Application Visibility

Catalyst 2960-X Series Switches support **NetFlow Lite**, which enables IT teams to understand the mix of traffic on their network and identify anomalies by capturing and recording specific packet flows. NetFlow Lite supports flexible sampling of the traffic, and exports flow data in the NetFlow Version 9 format for analysis on a wide range of Cisco and third-party collectors.

NetFlow Lite is included on all Catalyst 2960-X and 2960-XR LAN Base and IP Lite models.

Cisco Catalyst SmartOperations

Cisco Catalyst SmartOperations is a comprehensive set of capabilities that simplify LAN planning, deployment, monitoring, and troubleshooting. Deploying SmartOperations tools reduces the time and effort required to operate the network and lowers total cost of ownership (TCO).

- **Cisco Smart Install** services enable minimal-touch deployment by providing automated Cisco IOS Software image installation and configuration when new switches are connected to the network. This enables network administrators to remotely manage IOS image installs and upgrades.
- **Cisco Auto SmartPorts** services enable automatic configuration of switch ports as devices connect to the switch, with settings optimized for the device type resulting in zero-touch port-policy provisioning.
- **Cisco Auto QoS** is a service that automatic configuration of QoS that allows switch to manage QoS policies based on traffic types resulting in zero-touch traffic engineering.
- **Cisco Smart Troubleshooting** is an extensive array of diagnostic commands and system health checks within the switch, including Smart Call Home. The Cisco GOLD[®] (Generic Online Diagnostics) and Cisco online diagnostics on switches in live networks help predicting and detecting failures faster.

For more information about Cisco Catalyst SmartOperations, visit cisco.com/go/SmartOperations.

Operational Simplicity Features

- **Dynamic Host Configuration Protocol (DHCP)** autoconfiguration of multiple switches through a boot server eases switch deployment.
- **Stacking master configuration management** and Cisco FlexStack Plus technology helps ensure that all switches are automatically upgraded when the master switch receives a new software version. Automatic software version checking and updating help ensure that all stack members have the same software version.
- **Autonegotiation** on all ports automatically selects half- or full-duplex transmission mode to optimize bandwidth.

- **Dynamic Trunking Protocol (DTP)** facilitates dynamic trunk configuration across all switch ports.
- **Port Aggregation Protocol (PAgP)** automates the creation of Cisco Fast EtherChannel[®] groups or Gigabit EtherChannel groups to link to another switch, router, or server.
- **Link Aggregation Control Protocol (LACP)** allows the creation of Ethernet channeling with devices that conform to IEEE 802.3ad. This feature is similar to Cisco EtherChannel technology and PAgP.
- **Automatic media-dependent interface crossover (MDIX)** automatically adjusts transmit and receive pairs if an incorrect cable type (crossover or straight-through) is installed.
- **Unidirectional Link Detection Protocol (UDLD)** and Aggressive UDLD allow unidirectional links caused by incorrect fiber-optic wiring or port faults to be detected and disabled on fiber-optic interfaces.
- **Switching Database Manager (SDM)** templates for access, routing, and VLAN deployment allow the administrator to easily maximize memory allocation to the desired features based on deployment-specific requirements.
- **Local Proxy Address Resolution Protocol (ARP)** works in conjunction with Private VLAN Edge to minimize broadcasts and maximize available bandwidth.
- **VLAN1 minimization** allows VLAN1 to be disabled on any individual VLAN trunk.
- **Smart Multicast, with Cisco FlexStack-Plus technology**, allows the Cisco Catalyst 2960-X Series to offer greater efficiency and support for more multicast data streams such as video by putting each data packet onto the backplane only once.
- **Internet Group Management Protocol (IGMP) Snooping** for IPv4 and IPv6 MLD v1 and v2 Snooping provide fast client joins and leaves of multicast streams and limit bandwidth-intensive video traffic to only the requestors.
- **Multicast VLAN Registration (MVR)** continuously sends multicast streams in a multicast VLAN while isolating the streams from subscriber VLANs for bandwidth and security reasons.
- **Per-port broadcast, multicast, and unicast storm control** prevents faulty end stations from degrading overall systems performance.
- **Voice VLAN** simplifies telephony installations by keeping voice traffic on a separate VLAN for easier administration and troubleshooting.
- **Cisco VLAN Trunking Protocol (VTP)** supports dynamic VLANs and dynamic trunk configuration across all switches.
- **Remote Switch Port Analyzer (RSPAN)** allows administrators to remotely monitor ports in a Layer 2 switch network from any other switch in the same network.
- For enhanced traffic management, monitoring, and analysis, the Embedded **Remote Monitoring (RMON)** software agent supports four RMON groups (history, statistics, alarms, and events).
- **Layer 2 trace route** eases troubleshooting by identifying the physical path that a packet takes from source to destination.
- **Trivial File Transfer Protocol (TFTP)** reduces the cost of administering software upgrades by downloading from a centralized location.
- **Network Timing Protocol (NTP)** provides an accurate and consistent timestamp to all intranet switches.

Power Management

The 2960-X switches offer a range of industry leading features for effective energy efficiency and energy management.

Switch Hibernation Mode (SHM) is an industry first and available on all 2960-X series switches. This feature puts the switch in ultra low power mode during periods of non-operation such as nights or weekends. Switch Hibernation Mode on the 2960-X switches can be scheduled using EnergyWise compliant management software.

IEEE 802.3az EEE (Energy Efficient Ethernet) enables ports to dynamically sense idle periods between traffic bursts and quickly switch the interfaces into a low power idle mode, reducing power consumption.

Cisco EnergyWise policies can be used to control the power consumed by PoE-powered endpoints, desktop and data-center IT equipment, and a wide range of building infrastructure. EnergyWise technology is included on all Cisco Catalyst 2960-X Series Switches.

For more information about Cisco EnergyWise™, visit cisco.com/go/energywise.

Network Management

The Cisco Catalyst 2960-X Series Switches offer a superior CLI for detailed configuration and administration. 2960-X Series Switches are also supported in the full range of Cisco network management solutions.

Cisco Prime Infrastructure

Cisco Prime™ network management solutions provide comprehensive network lifecycle management. Cisco Prime Infrastructure provides an extensive library of easy-to-use features to automate the initial and day-to-day management of your Cisco network. Cisco Prime integrates hardware and software platform expertise and operational experience into a powerful set of workflow-driven configuration, monitoring, troubleshooting, reporting, and administrative tools.

For detailed information about Cisco Prime, visit cisco.com/go/prime.

Cisco Network Assistant

A Cisco network management application designed for small and medium-sized business (SMB) networks with up to 250 users that runs on PCs, Tablets and even SmartPhones, Cisco Network Assistant offers centralized network management and configuration capabilities. This application also features an intuitive GUI where users can easily apply common services across Cisco switches, routers, and access points.

For detailed information about Cisco Network Assistant, visit cisco.com/go/cna.

Security Management

Cisco Identity Services Engine (ISE) support enables the 2960-XR switches to offer security management for all devices connected to it.

Technical Specifications

Table 8. Cisco Catalyst 2960-X Series Hardware

| Hardware Specifications | |
|------------------------------|---|
| Flash memory | 128 MB for LAN Base & IP Lite SKUs, 64 MB for LAN Lite SKUs |
| DRAM | 512 MB |
| CPU | APM86392 600MHz dual core |
| Console Ports | USB (Type-B), Ethernet (RJ-45) |
| Storage Interface | USB (Type-A) for external flash storage |
| Network Management Interface | 10/100 Mbps Ethernet (RJ-45) |

Table 9. Cisco Catalyst 2960-X Series Performance

| Performance and Scalability | | | |
|---|-----------------|-----------------|-----------------|
| | 2960-X LAN Lite | 2960-X LAN Base | 2960-XR IP Lite |
| Forwarding bandwidth | 50 Gbps | 108 Gbps | 108 Gbps |
| Switching bandwidth* | 100 Gbps | 216 Gbps | 216 Gbps |
| Maximum active VLANs | 64 | 1023 | 1023 |
| VLAN IDs available | 4096 | 4096 | 4096 |
| Maximum transmission unit (MTU) - L3 packet | 9198 bytes | 9198 bytes | 9198 bytes |
| Jumbo frame - Ethernet frame | 9216 bytes | 9216 bytes | 9216 bytes |

* Switching bandwidth is full-duplex capacity.

Table 10. Cisco Catalyst 2960-X Series Forwarding Performance

| Forwarding Rate: 64-Byte L3 Packets | |
|-------------------------------------|------------|
| Catalyst 2960-X Family | |
| Cisco Catalyst 2960X-48FPD-L | 130.9 Mpps |
| Cisco Catalyst 2960X-48LPD-L | 130.9 Mpps |
| Cisco Catalyst 2960X-24PD-L | 95.2 Mpps |
| Cisco Catalyst 2960X-48TD-L | 130.9 Mpps |
| Cisco Catalyst 2960X-24TD-L | 95.2 Mpps |
| Cisco Catalyst 2960X-48FPS-L | 107.1 Mpps |
| Cisco Catalyst 2960X-48LPS-L | 107.1 Mpps |
| Cisco Catalyst 2960X-24PS-L | 71.4 Mpps |
| Cisco Catalyst 2960X-24PSQ-L | 71.4 Mpps |
| Cisco Catalyst 2960X-48TS-L | 107.1 Mpps |
| Cisco Catalyst 2960X-24TS-L | 71.4 Mpps |
| Cisco Catalyst 2960X-48TS-LL | 104.2 Mpps |
| Cisco Catalyst 2960X-24TS-LL | 68.5 Mpps |
| Catalyst 2960-XR Family | |
| Cisco Catalyst 2960XR-48FPD-I | 130.9 Mpps |
| Cisco Catalyst 2960XR-48LPD-I | 130.9 Mpps |
| Cisco Catalyst 2960XR-24PD-I | 95.2 Mpps |
| Cisco Catalyst 2960XR-48TD-I | 130.9 Mpps |
| Cisco Catalyst 2960XR-24TD-I | 95.2 Mpps |

| Forwarding Rate: 64-Byte L3 Packets | |
|-------------------------------------|------------|
| Cisco Catalyst 2960XR-48FPS-I | 107.1 Mpps |
| Cisco Catalyst 2960XR-48LPS-I | 107.1 Mpps |
| Cisco Catalyst 2960XR-24PS-I | 71.4 Mpps |
| Cisco Catalyst 2960XR-48TS-I | 107.1 Mpps |
| Cisco Catalyst 2960XR-24TS-I | 71.4 Mpps |

Table 11. Cisco Catalyst 2960-X Series Mechanical Specifications

| Models | | |
|-------------------|---------------------|-------------------------|
| Dimensions | Inches (H x D x W) | Centimeters (H x D x W) |
| WS-C2960X-48FPD-L | 1.75 x 14.5 x 17.5 | 4.5 x 36.8 x 44.5 |
| WS-C2960X-48LPD-L | 1.75 x 14.5 x 17.5 | 4.5 x 36.8 x 44.5 |
| WS-C2960X-48TD-L | 1.75 x 11.0 x 17.5 | 4.5 x 27.9 x 44.5 |
| WS-C2960X-24PD-L | 1.75 x 14.5 x 17.5 | 4.5 x 36.8 x 44.5 |
| WS-C2960X-24TD-L | 1.75 x 11.0 x 17.5 | 4.5 x 27.9 x 44.5 |
| WS-C2960X-48FPS-L | 1.75 x 14.5 x 17.5 | 4.5 x 36.8 x 44.5 |
| WS-C2960X-48LPS-L | 1.75 x 14.5 x 17.5 | 4.5 x 36.8 x 44.5 |
| WS-C2960X-48TS-L | 1.75 x 11.0 x 17.5 | 4.5 x 27.9 x 44.5 |
| WS-C2960X-24PS-L | 1.75 x 14.5 x 17.5 | 4.5 x 36.8 x 44.5 |
| WS-C2960X-24PSQ-L | 1.73 x 11.03 x 17.5 | 4.45 x 28.0 x 44.5 |
| WS-C2960X-24TS-L | 1.75 x 11.0 x 17.5 | 4.5 x 27.9 x 44.5 |
| WS-C2960X-48TS-LL | 1.75 x 11.0 x 17.5 | 4.5 x 27.9 x 44.5 |
| WS-C2960X-24TS-LL | 1.75 x 11.0 x 17.5 | 4.5 x 27.9 x 44.5 |
| Weights | Pounds | Kilograms |
| WS-C2960X-48FPD-L | 12.9 lbs | 5.8 Kg |
| WS-C2960X-48LPD-L | 12.9 lbs | 5.8 Kg |
| WS-C2960X-48TD-L | 9.6 lbs | 4.3 Kg |
| WS-C2960X-24PD-L | 12.7 lbs | 5.7 Kg |
| WS-C2960X-24TD-L | 8.9 lbs | 4.0 Kg |
| WS-C2960X-48FPS-L | 12.9 lbs | 5.8 Kg |
| WS-C2960X-48LPS-L | 12.9 lbs | 5.8 Kg |
| WS-C2960X-48TS-L | 9.4 lbs | 4.2 Kg |
| WS-C2960X-24PS-L | 12.8 lbs | 5.8 kg |
| WS-C2960X-24PSQ-L | 12.8 lbs | 5.8 kg |
| WS-C2960X-24TS-L | 8.9 lbs | 4.0 kg |
| WS-C2960X-48TS-LL | 8.9 lbs | 4.0kg |
| WS-C2960X-24TS-LL | 8.2 lbs | 3.7 kg |

Table 12. Cisco Catalyst 2960-XR Series Mechanical Specifications

| Models | | |
|--------------------|--------------------|-------------------------|
| Dimensions | Inches (H x D x W) | Centimeters (H x D x W) |
| WS-C2960XR-48FPD-I | 1.75 x 16.0 x 17.5 | 4.45 x 40.8 x 44.5 |
| WS-C2960XR-48LPD-I | 1.75 x 16.0 x 17.5 | 4.45 x 40.8 x 44.5 |
| WS-C2960XR-48TD-I | 1.75 x 16.0 x 17.5 | 4.45 x 40.8 x 44.5 |
| WS-C2960XR-24PD-I | 1.75 x 16.0 x 17.5 | 4.45 x 40.8 x 44.5 |
| WS-C2960XR-24TD-I | 1.75 x 16.0 x 17.5 | 4.45 x 40.8 x 44.5 |
| WS-C2960XR-48FPS-I | 1.75 x 16.0 x 17.5 | 4.45 x 40.8 x 44.5 |
| WS-C2960XR-48LPS-I | 1.75 x 16.0x 17.5 | 4.45 x 40.8 x 44.5 |
| WS-C2960XR-48TS-I | 1.75 x 16.0 x 17.5 | 4.45 x 40.8 x 44.5 |
| WS-C2960XR-24PS-I | 1.75 x 16.0 x 17.5 | 4.45 x 40.8 x 44.5 |
| WS-C2960XR-24TS-I | 1.75 x 16.0 x 17.5 | 4.45 x 40.8 x 44.5 |
| Weights | Pounds | Kilograms |
| WS-C2960XR-48FPD-I | 14.6 | 6.6 |
| WS-C2960XR-48LPD-I | 14.0 | 6.4 |
| WS-C2960XR-48TD-I | 13.3 | 6.1 |
| WS-C2960XR-24PD-I | 13.6 | 6.2 |
| WS-C2960XR-24TD-I | 13.0 | 5.9 |
| WS-C2960XR-48FPS-I | 14.7 | 6.7 |
| WS-C2960XR-48LPS-I | 14.2 | 6.4 |
| WS-C2960XR-48TS-I | 13.2 | 6.0 |
| WS-C2960XR-24PS-I | 13.7 | 6.2 |
| WS-C2960XR-24TS-I | 13.0 | 5.9 |

Table 13. Cisco Catalyst 2960-X Series Environmental Specifications

| Environmental Ranges | | |
|--|--------------------------|--------------|
| | Fahrenheit | Centigrade |
| Operating temperature up to 5000 ft (1500 m) | 23°F to 113°F | -5°C to 45°C |
| Operating temperature up to 10,000 ft (3000 m) | 23°F to 104°F | -5°C to 40°C |
| Short-term exception at sea level [†] | 23°F to 131°F | -5°C to 55°C |
| Short-term exception up to 5000 feet (1500 m) [†] | 23°F to 122°F | -5°C to 50°C |
| Short-term exception up to 10,000 feet (3000 m) [†] | 23°F to 113°F | -5°C to 45°C |
| Short-term exception up to 13,000 feet (4000 m) [†] | 23° to 104°F | -5°C to 40°C |
| Storage temperature up to 15,000 feet (4573 m) | -13° to 158°F | -25° to 70°C |
| | Feet | Meters |
| Operating altitude | Up to 10,000 | Up to 3000 |
| Storage altitude | Up to 13,000 | Up to 4000 |
| Operating relative humidity | 10% to 95% noncondensing | |
| Storage relative humidity | 10% to 95% noncondensing | |
| Acoustic Noise | | |
| <i>Measured per ISO 7779 and declared per ISO 9296.</i> | | |
| <i>Bystander positions operating mode at 25°C ambient.</i> | | |

| Environmental Ranges | | | | |
|-------------------------------|----------------------------|----------------|---------------|----------------|
| Model | Sound Pressure | | Sound Power | |
| | LpA (Typical) | LpAD (Maximum) | LwA (Typical) | LwAD (Maximum) |
| Cisco Catalyst 2960X-48FPD-L | 39 dB | 43 dB | 4.9 B | 5.3 B |
| Cisco Catalyst 2960X-48LPD-L | | | | |
| Cisco Catalyst 2960X-24PD-L | | | | |
| Cisco Catalyst 2960X-48TD-L | 42 dB | 46 dB | 5.1 B | 5.5 B |
| Cisco Catalyst 2960X-24TD-L | | | | |
| Cisco Catalyst 2960X-48FPS-L | 39 dB | 43 dB | 4.9 B | 5.3 B |
| Cisco Catalyst 2960X-48LPS-L | | | | |
| Cisco Catalyst 2960X-24PS-L | | | | |
| Cisco Catalyst 2960X-24PSQ-L | N/A | N/A | N/A | N/A |
| Cisco Catalyst 2960X-48TS-L | 42 dB | 46 dB | 5.1 B | 5.5 B |
| Cisco Catalyst 2960X-24TS-L | | | | |
| Cisco Catalyst 2960X-48TS-LL | 42 dB | 46 dB | 5.1 B | 5.5 B |
| Cisco Catalyst 2960X-24TS-LL | | | | |
| Cisco Catalyst 2960XR-48FPD-I | 40dB | 43dB | 5.2B | 5.5B |
| Cisco Catalyst 2960XR-48LPD-I | 40dB | 43dB | 5.2B | 5.5B |
| Cisco Catalyst 2960XR-24PD-I | 40dB | 43dB | 5.2B | 5.5B |
| Cisco Catalyst 2960XR-48TD-I | 22dB | 25dB | 3.3B | 3.6B |
| Cisco Catalyst 2960XR-24TD-I | 22dB | 25dB | 3.3B | 3.6B |
| Cisco Catalyst 2960XR-48FPS-I | 40dB | 43dB | 5.2B | 5.5B |
| Cisco Catalyst 2960XR-48LPS-I | 40dB | 43dB | 5.2B | 5.5B |
| Cisco Catalyst 2960XR-24PS-I | 40dB | 43dB | 5.2B | 5.5B |
| Cisco Catalyst 2960XR-48TS-I | 22dB | 25dB | 3.3B | 3.6B |
| Cisco Catalyst 2960XR-24TS-I | 22dB | 25dB | 3.3B | 3.6B |
| Predicted Reliability | | | | |
| Model | MTBF in hours [™] | | | |
| Cisco Catalyst 2960X-48FPD-L | 233,370 | | | |
| Cisco Catalyst 2960X-48LPD-L | 277,960 | | | |
| Cisco Catalyst 2960X-24PD-L | 325,780 | | | |
| Cisco Catalyst 2960X-48TD-L | 445,460 | | | |
| Cisco Catalyst 2960X-24TD-L | 569,520 | | | |
| Cisco Catalyst 2960X-48FPS-L | 232,610 | | | |
| Cisco Catalyst 2960X-48LPS-L | 276,870 | | | |
| Cisco Catalyst 2960X-24PS-L | 324,280 | | | |
| Cisco Catalyst 2960X-24PSQ-L | 462,680 | | | |
| Cisco Catalyst 2960X-48TS-L | 442,690 | | | |
| Cisco Catalyst 2960X-24TS-L | 564,910 | | | |
| Cisco Catalyst 2960X-48TS-LL | 476,560 | | | |
| Cisco Catalyst 2960X-24TS-LL | 622,350 | | | |
| Cisco Catalyst 2960X-STACK | 17,128,090 | | | |
| Cisco Catalyst 2960XR-48FPD-I | 231,590 | | | |
| Cisco Catalyst 2960XR-48LPD-I | 275,430 | | | |
| Cisco Catalyst 2960XR-24PD-I | 322,740 | | | |
| Cisco Catalyst 2960XR-48TD-I | 440,880 | | | |

| Environmental Ranges | |
|-------------------------------|-----------|
| Cisco Catalyst 2960XR-24TD-I | 561,890 |
| Cisco Catalyst 2960XR-48FPS-I | 230,860 |
| Cisco Catalyst 2960XR-48LPS-I | 274,380 |
| Cisco Catalyst 2960XR-24PS-I | 321,290 |
| Cisco Catalyst 2960XR-48TS-I | 438,130 |
| Cisco Catalyst 2960XR-24TS-I | 557,320 |
| Cisco PWR-C2-250WAC | 1,000,000 |
| Cisco PWR-C2-640WAC | 1,000,000 |
| Cisco PWR-C2-1025WAC | 1,000,000 |

* Not more than the following in a 1-year period: 96 consecutive hours, or 360 hours total, or 15 occurrences.

** Currently estimates; Later will be Based on Telcordia SR-332 Issue 2 methodology.

Table 14. Connectors and Interfaces

| Connectors and Interfaces |
|---|
| Ethernet Interfaces <ul style="list-style-type: none"> • 10BASE-T ports: RJ-45 connectors, 2-pair Category 3, 4, or 5 unshielded twisted-pair (UTP) cabling • 100BASE-TX ports: RJ-45 connectors, 2-pair Category 5 UTP cabling • 1000BASE-T ports: RJ-45 connectors, 4-pair Category 5 UTP cabling • 1000BASE-T SFP-based ports: RJ-45 connectors, 4-pair Category 5 UTP cabling |
| SFP and SFP+ Interfaces <p>For information about supported SFP/SFP+ modules, refer to the Transceiver Compatibility matrix tables at cisco.com/en/US/products/hw/modules/ps5455/products_device_support_tables_list.html.</p> |
| Indicator LEDs <ul style="list-style-type: none"> • Per-port status: Link integrity, disabled, activity, speed, and full duplex • System status: System, RPS, Stack link status, link duplex, PoE, and link speed |
| Stacking Interfaces <p>Cisco Catalyst 2960-XFlexStack-Plus stacking cables:</p> <ul style="list-style-type: none"> • CAB-STK-E-0.5M FlexStack-Plus stacking cable with a 0.5 m length • CAB-STK-E-1M FlexStack-Plus stacking cable with a 1.0 m length • CAB-STK-E-3M FlexStack-Plus stacking cable with a 3.0 m length |
| Console <p>Cisco Catalyst 2960-X console cables:</p> <ul style="list-style-type: none"> • CAB-CONSOLE-RJ45 Console cable 6 ft. with RJ-45 • CAB-CONSOLE-USB Console cable 6 ft. with USB Type A and mini-B connectors |
| Power <ul style="list-style-type: none"> • The internal power supply is an auto-ranging unit and supports input voltages between 100 and 240V AC • Use the supplied AC power cord to connect the AC power connector to an AC power outlet • The Cisco RPS connector offers connection for an optional Cisco RPS 2300 that uses AC input and supplies DC output to the switch • Only the Cisco RPS 2300 (model PWR-RPS2300) should be attached to the redundant-power-system receptacle |

Table 15. Management and Standards Support

| Category | Specification | |
|---|---|---|
| Management | <ul style="list-style-type: none"> • BRIDGE-MIB • CISCO-CABLE-DIAG-MIB • CISCO-CDP-MIB • CISCO-CLUSTER-MIB • CISCO-CONFIG-COPY-MIB • CISCO-CONFIG-MAN-MIB • CISCO-DHCP-SNOOPING-MIB • CISCO-ENTITY-VENDORTYPE-OID-MIB • CISCO-ENVMON-MIB • CISCO-ERR-DISABLE-MIB • CISCO-FLASH-MIB • CISCO-FTP-CLIENT-MIB • CISCO-IGMP-FILTER-MIB • CISCO-IMAGE-MIB • CISCO-IP-STAT-MIB • CISCO-LAG-MIB • CISCO-MAC-NOTIFICATION-MIB • CISCO-MEMORY-POOL-MIB • CISCO-PAGP-MIB • CISCO-PING-MIB • CISCO-POE-EXTENSIONS-MIB • CISCO-PORT-QOS-MIB • CISCO-PORT-SECURITY-MIB • CISCO-PORT-STORM-CONTROL-MIB • CISCO-PRODUCTS-MIB • CISCO-PROCESS-MIB • CISCO-RTTMON-MIB • CISCO-SMI-MIB • CISCO-STP-EXTENSIONS-MIB • CISCO-SYSLOG-MIB | <ul style="list-style-type: none"> • CISCO-TC-MIB • CISCO-TCP-MIB • CISCO-UDLDP-MIB • CISCO-VLAN-IFTABLE • RELATIONSHIP-MIB • CISCO-VLAN-MEMBERSHIP-MIB • CISCO-VTP-MIB • ENTITY-MIB • ETHERLIKE-MIB • IEEE8021-PAE-MIB • IEEE8023-LAG-MIB • IF-MIB • INET-ADDRESS-MIB • OLD-CISCO-CHASSIS-MIB • OLD-CISCO-FLASH-MIB • OLD-CISCO-INTERFACES-MIB • OLD-CISCO-IP-MIB • OLD-CISCO-SYS-MIB • OLD-CISCO-TCP-MIB • OLD-CISCO-TS-MIB • RFC1213-MIB • RMON-MIB • RMON2-MIB • SNMP-FRAMEWORK-MIB • SNMP-MPD-MIB • SNMP-NOTIFICATION-MIB • SNMP-TARGET-MIB • SNMPv2-MIB • TCP-MIB • UDP-MIB • ePM MIB • CISCO-FLEXSTACK-PLUS-MIB (2960-X) |
| For an updated list of supported MIBs, refer to the MIB Locator at cisco.com/go/mibs . | | |
| Standards | <ul style="list-style-type: none"> • IEEE 802.1D Spanning Tree Protocol • IEEE 802.1p CoS Prioritization • IEEE 802.1Q VLAN • IEEE 802.1s • IEEE 802.1w • IEEE 802.1X • IEEE 802.1ab (LLDP) • IEEE 802.3ad • IEEE 802.3af and IEEE 802.3at • IEEE 802.3ah (100BASE-X single/multimode fiber only) • IEEE 802.3x full duplex on 10BASE-T, 100BASE-TX, and 1000BASE-T ports | <ul style="list-style-type: none"> • IEEE 802.3 10BASE-T • IEEE 802.3u 100BASE-TX • IEEE 802.3ab 1000BASE-T • IEEE 802.3z 1000BASE-X • RMON I and II standards • SNMP v1, v2c, and v3 • IEEE 802.3az • IEEE 802.3ae 10Gigabit Ethernet • IEEE 802.1ax |

| Category | Specification |
|-----------------------|---|
| RFC compliance | <ul style="list-style-type: none"> • RFC 768 - UDP • RFC 783 - TFTP • RFC 791 - IP • RFC 792 - ICMP • RFC 793 - TCP • RFC 826 - ARP • RFC 854 - Telnet • RFC 951 - Bootstrap Protocol (BOOTP) • RFC 959 - FTP • RFC 1112 - IP Multicast and IGMP • RFC 1157 - SNMP v1 • RFC 1166 - IP Addresses • RFC 1256 - Internet Control Message Protocol (ICMP) Router Discovery • RFC 1305 - NTP • RFC 1492 - TACACS+ • RFC 1493 - Bridge MIB • RFC 1542 - BOOTP extensions • RFC 1643 - Ethernet Interface MIB • RFC 1757 - RMON <ul style="list-style-type: none"> • RFC 1901 - SNMP v2C • RFC 1902-1907 - SNMP v2 • RFC 1981 - Maximum Transmission Unit (MTU) Path Discovery IPv6 • RFC 2068 - HTTP • RFC 2131 - DHCP • RFC 2138 - RADIUS • RFC 2233 - IF MIB v3 • RFC 2373 - IPv6 Aggregatable Addrs • RFC 2460 - IPv6 • RFC 2461 - IPv6 Neighbor Discovery • RFC 2462 - IPv6 Autoconfiguration • RFC 2463 - ICMP IPv6 • RFC 2474 - Differentiated Services (DiffServ) Precedence • RFC 2597 - Assured Forwarding • RFC 2598 - Expedited Forwarding • RFC 2571 - SNMP Management • RFC 3046 - DHCP Relay Agent Information Option • RFC 3376 - IGMP v3 • RFC 3580 - 802.1X RADIUS |

Table 16. Voltage and Power Ratings

| Input Voltage and Current | | | |
|-------------------------------|------------------------|----------------|------------|
| Model | Voltage (Auto ranging) | Current | Frequency |
| Cisco Catalyst 2960X-48FPD-L | 100 to 240 VAC | 9A-4A | 50 to 60Hz |
| Cisco Catalyst 2960X-48LPD-L | | 5A-2A | |
| Cisco Catalyst 2960X-24PD-L | | 5A-2A | |
| Cisco Catalyst 2960X-48TD-L | | 1A - 0.5A | |
| Cisco Catalyst 2960X-24TD-L | | 1A to 0.5A | |
| Cisco Catalyst 2960X-48FPS-L | | 9A - 4A | |
| Cisco Catalyst 2960X-48LPS-L | | 5A - 2A | |
| Cisco Catalyst 2960X-24PS-L | | 5A - 2A | |
| Cisco Catalyst 2960X-24PSQ-L | | 2A - 4A | |
| Cisco Catalyst 2960X-48TS-L | | 1A-0.5A | |
| Cisco Catalyst 2960X-24TS-L | | 1A - 0.5A | |
| Cisco Catalyst 2960X-48TS-LL | | 1A - 0.5A | |
| Cisco Catalyst 2960X-24TS-LL | | 1A - 0.5A | |
| Cisco Catalyst 2960XR-48FPD-I | | 100 to 240 VAC | |
| Cisco Catalyst 2960XR-48LPD-I | 6A to 3 A | | |
| Cisco Catalyst 2960XR-24PD-I | 6A to 3 A | | |
| Cisco Catalyst 2960XR-48TD-I | 1A to 0.5 A | | |
| Cisco Catalyst 2960XR-24TD-I | 1A to 0.5 A | | |
| Cisco Catalyst 2960XR-48FPS-I | 10A to 5 A | | |
| Cisco Catalyst 2960XR-48LPS-I | 6A to 3 A | | |
| Cisco Catalyst 2960XR-24PS-I | 6A to 3 A | | |
| Cisco Catalyst 2960XR-48TS-I | 1A to 0.5 A | | |
| Cisco Catalyst 2960XR-24TS-I | 1A to 0.5 A | | |

| Power Rating (Switch maximum consumption values) | |
|--|-----------|
| Cisco Catalyst 2960X-48FPD-L | 0.89 kVA |
| Cisco Catalyst 2960X-48LPD-L | 0.48 kVA |
| Cisco Catalyst 2960X-24PD-L | 0.47 kVA |
| Cisco Catalyst 2960X-48TD-L | 0.049 kVA |
| Cisco Catalyst 2960X-24TD-L | 0.034 kVA |
| Cisco Catalyst 2960X-48FPS-L | 0.89 kVA |
| Cisco Catalyst 2960X-48LPS-L | 0.49 kVA |
| Cisco Catalyst 2960X-24PS-L | 0.49 kVA |
| Cisco Catalyst 2960X-24PSQ-L | 0.16 kVA |
| Cisco Catalyst 2960X-48TS-L | 0.051 kVA |
| Cisco Catalyst 2960X-24TS-L | 0.039 kVA |
| Cisco Catalyst 2960X-48TS-LL | 0.46KVA |
| Cisco Catalyst 2960X-24TS-LL | 0.035KVA |
| Cisco Catalyst 2960XR-48FPD-I | 0.89KVA |
| Cisco Catalyst 2960XR-48LPD-I | 0.48KVA |
| Cisco Catalyst 2960XR-24PD-I | 0.46KVA |
| Cisco Catalyst 2960XR-48TD-I | 0.047KVA |
| Cisco Catalyst 2960XR-24TD-I | 0.039KVA |
| Cisco Catalyst 2960XR-48FPS-I | 0.89KVA |
| Cisco Catalyst 2960XR-48LPS-I | 0.47KVA |
| Cisco Catalyst 2960XR-24PS-I | 0.46KVA |
| Cisco Catalyst 2960XR-48TS-I | 0.046KVA |
| Cisco Catalyst 2960XR-24TS-I | 0.038KVA |

| DC Input Voltages (RPS Input) - Only for 2960-X LAN Base Switches | | |
|---|-----|-----|
| | 12V | 53V |
| Cisco Catalyst 2960X-48FPD-L | 4A | 15A |
| Cisco Catalyst 2960X-48LPD-L | 4A | 8A |
| Cisco Catalyst 2960X-24PD-L | 3A | 8A |
| Cisco Catalyst 2960X-48TD-L | 4A | N/A |
| Cisco Catalyst 2960X-24TD-L | 3A | N/A |
| Cisco Catalyst 2960X-48FPS-L | 4A | 15A |
| Cisco Catalyst 2960X-48LPS-L | 4A | 8A |
| Cisco Catalyst 2960X-24PS-L | 3A | 8A |
| Cisco Catalyst 2960X-24PSQ-L | N/A | N/A |
| Cisco Catalyst 2960X-48TS-L | 5A | N/A |
| Cisco Catalyst 2960X-24TS-L | 4A | N/A |

Note: The wattage rating on the power supply does not represent actual power draw. It indicates the maximum power draw possible by the power supply. This rating can be used for facility capacity planning. For PoE switches, cooling requirements are smaller than total power draw as a significant portion of the load is dissipated in the endpoints.

Table 17. Power Consumption¹

| Measured Power Consumption in Watts ² | | | | |
|--|-------------------------|-------------|--------------|------------------|
| Model | 0% Traffic ³ | 10% Traffic | 100% Traffic | Weighted Average |
| Cisco Catalyst 2960X-48FPD-L | 50.8 | 65.9 | 66.7 | 66.0 |
| Cisco Catalyst 2960X-48LPD-L | 45.7 | 61.1 | 62.0 | 61.2 |
| Cisco Catalyst 2960X-24PD-L | 44.7 | 52.3 | 53.1 | 52.3 |
| Cisco Catalyst 2960X-48TD-L | 32.9 | 47.0 | 47.8 | 47.1 |
| Cisco Catalyst 2960X-24TD-L | 24.9 | 32.2 | 33.1 | 32.3 |
| Cisco Catalyst 2960X-48FPS-L | 51.9 | 66.6 | 66.8 | 66.6 |
| Cisco Catalyst 2960X-48LPS-L | 46.7 | 60.8 | 61.1 | 60.9 |
| Cisco Catalyst 2960X-24PS-L | 41.4 | 49.0 | 49.2 | 49.0 |
| Cisco Catalyst 2960X-24PSQ-L | 28.5 | 32.8 | 34.8 | 33.0 |
| Cisco Catalyst 2960X-48TS-L | 34.9 | 49.5 | 49.7 | 49.5 |
| Cisco Catalyst 2960X-24TS-L | 28.0 | 36.8 | 37.1 | 36.9 |
| Cisco Catalyst 2960X-48TS-LL | 31.4 | 44.3 | 44.5 | 44.4 |
| Cisco Catalyst 2960X-24TS-LL | 25.2 | 32.0 | 32.0 | 32.0 |
| Cisco Catalyst 2960XR-48FPD-I | 46.7 | 61.8 | 62.5 | 61.9 |
| Cisco Catalyst 2960XR-48LPD-I | 40.7 | 54.6 | 55.9 | 54.8 |
| Cisco Catalyst 2960XR-24PD-I | 36.1 | 42.9 | 43.7 | 43.0 |
| Cisco Catalyst 2960XR-48TD-I | 29.7 | 44.7 | 45.6 | 44.8 |
| Cisco Catalyst 2960XR-24TD-I | 29.3 | 37.2 | 38.1 | 37.3 |
| Cisco Catalyst 2960XR-48FPS-I | 44.8 | 58.5 | 58.8 | 58.5 |
| Cisco Catalyst 2960XR-48LPS-I | 37.9 | 52.8 | 53.0 | 52.9 |
| Cisco Catalyst 2960XR-24PS-I | 36.5 | 43.2 | 43.4 | 43.2 |
| Cisco Catalyst 2960XR-48TS-I | 30.0 | 44.8 | 45.0 | 44.8 |
| Cisco Catalyst 2960XR-24TS-I | 28.8 | 36.0 | 36.2 | 36.0 |

Table 18. Safety and Compliance

| Specification | Description |
|------------------------|---|
| Safety | UL 60950-1 Second Edition CAN/CSA-C22.2 No. 60950-1 Second Edition EN 60950-1 Second Edition IEC 60950-1 Second Edition AS/NZS 60950-1 |
| EMC - Emissions | 47CFR Part 15 (CFR 47) Class A AS/NZS CISPR22 Class A CISPR22 Class A EN55022 Class A ICES003 Class A VCCI Class A EN61000-3-2 EN61000-3-3 KN22 Class A CNS13438 Class A |

¹ Disclaimer: All power consumption numbers were measured under controlled laboratory conditions and are provided as estimates.

² ATIS Methodology

³ All Traffic measured with EEE enabled.

| Specification | Description |
|-------------------------------------|---|
| EMC - Immunity | EN55024 CISPR24 EN300386 KN24 |
| Environmental | Reduction of Hazardous Substances (RoHS) including Directive 2011/65/EU |
| Telco | Common Language Equipment Identifier (CLEI) code |
| US Government Certifications | USGv6 and IPv6 Ready Logo |

Cisco Enhanced Limited Lifetime Hardware Warranty

Cisco Catalyst 2960-X Series Switches come with an enhanced limited lifetime warranty (E-LLW). The E-LLW provides the same terms as Cisco's standard limited lifetime warranty but adds next business day delivery of replacement hardware, where available, and 90 days of 8X5 Cisco Technical Assistance Center (TAC) support.

Your formal warranty statement, including the warranty applicable to Cisco software, appears in the Cisco information packet that accompanies your Cisco product. We encourage you to review carefully the warranty statement shipped with your specific product before use.

Cisco reserves the right to refund the purchase price as its exclusive warranty remedy. For further information about warranty terms, visit <http://www.cisco.com/go/warranty>.

Table 19. Warranty Terms

| Cisco Enhanced Limited Lifetime Hardware Warranty | |
|---|---|
| Device covered | Applies to all Cisco Catalyst 2960-X Series Switches. |
| Warranty duration | As long as the original end user continues to own or use the product. |
| End-of-life policy | In the event of discontinuance of product manufacture, Cisco warranty support is limited to five (5) years from the announcement of discontinuance. |
| Hardware replacement | Cisco or its service center will use commercially reasonable efforts to ship a Cisco Catalyst 2960-X replacement part for next business day delivery, where available. Otherwise, a replacement will be shipped within ten (10) working days after the receipt of the RMA request. Actual delivery times may vary depending on customer location. |
| Effective date | Hardware warranty commences from the date of shipment to customer (and in case of resale by a Cisco reseller, not more than ninety [90] days after original shipment by Cisco). |
| TAC support | Cisco will provide during customer's local business hours, 8 hours per day, 5 days per week basic configuration, diagnosis, and troubleshooting of device-level problems for up to 90 days from the date of shipment of the originally purchased Cisco Catalyst 2960-X product. This support does not include solution or network-level support beyond the specific device under consideration. |
| Cisco.com Access | Warranty allows guest access only to Cisco.com. |

Software Policy

Customers with Cisco Catalyst IP Lite, LAN Base and LAN Lite software feature sets will be provided with maintenance updates and bug fixes designed to maintain the compliance of the software with published specifications, release notes, and industry standards compliance as long as the original end user continues to own or use the product or up to one year from the end-of-sale date for this product, whichever occurs earlier.

This policy supersedes any previous warranty or software statement and is subject to change without notice.

Technical Support and Services

Table 20. Technical Services Available for Cisco Catalyst 2960-X Series Switches

| Technical Services |
|--|
| <p>Cisco SMARTnet Service</p> <ul style="list-style-type: none"> • Around-the-clock, global access to the Cisco TAC • Unrestricted access to the extensive Cisco.com knowledge base and tools • Next-business-day, 8x5x4, 24x7x4, or 24x7x2 advance hardware replacement and onsite parts replacement and installation available¹ • Ongoing operating system software updates within the licensed feature set² • Proactive diagnostics and real-time alerts on Smart Call Home enabled devices |
| <p>Cisco Smart Foundation Service</p> <ul style="list-style-type: none"> • Next-business-day advance hardware replacement as available • Access to SMB TAC during business hours (access levels vary by region) • Access to Cisco.com SMB knowledge base • Online technical resources through Smart Foundation Portal • Operating system software bug fixes and patches |
| <p>Cisco Smart Care Service</p> <ul style="list-style-type: none"> • Network-level coverage for the needs of small and medium-sized businesses • Proactive health checks and periodic assessments of Cisco network foundation, voice, and security technologies • Technical support for eligible Cisco hardware and software through Smart Care Portal • Cisco operating system and application software updates and upgrades² • Next-business-day advance hardware replacement as available, 24x7x4 option available¹ |
| <p>Cisco SP Base Service</p> <ul style="list-style-type: none"> • Around-the-clock, global access to the Cisco TAC • Registered access to Cisco.com • Next-business-day, 8x5x4, 24x7x4, and 24x7x2 advance hardware replacement. Return to factory option available¹ • Ongoing operating system software updates² |
| <p>Cisco Focused Technical Support Services</p> <p>Three levels of premium, high-touch services are available:</p> <ul style="list-style-type: none"> • Cisco High-Touch Operations Management Service • Cisco High-Touch Technical Support Service • Cisco High-Touch Engineering Service <p>Valid Cisco SMARTnet or SP Base contracts are required on all network equipment</p> |

¹ Advance hardware replacement is available in various service-level combinations. For example, 8x5xNBD indicates that shipment will be initiated during the standard 8-hour business day, 5 days a week (the generally accepted business days within the relevant region), with next-business-day (NBD) delivery. Where NBD is not available, same day shipping is provided. Restrictions apply; please review the appropriate service descriptions for details.

² Cisco operating system updates include the following: maintenance releases, minor updates, and major updates within the licensed feature set.

Ordering Information

Table 21. Cisco Catalyst 2960-X Series Switches Ordering Information

| Part Number | 10/100/1000 Ethernet Interfaces | Uplink Interfaces | Cisco IOS Software Feature Set | Available PoE Power | FlexStack-Plus Stacking |
|-------------------|---------------------------------|-------------------|--------------------------------|---------------------|-------------------------|
| WS-C2960X-48FPD-L | 48 | 2 SFP+ | LAN Base | 740W | Optional |
| WS-C2960X-48LPD-L | 48 | 2 SFP+ | LAN Base | 370W | Optional |
| WS-C2960X-24PD-L | 24 | 2 SFP+ | LAN Base | 370W | Optional |
| WS-C2960X-48TD-L | 48 | 2 SFP+ | LAN Base | - | Optional |
| WS-C2960X-24TD-L | 24 | 2 SFP+ | LAN Base | - | Optional |
| WS-C2960X-48FPS-L | 48 | 4 SFP | LAN Base | 740W | Optional |

| Part Number | 10/100/1000 Ethernet Interfaces | Uplink Interfaces | Cisco IOS Software Feature Set | Available PoE Power | FlexStack-Plus Stacking |
|-------------------|---------------------------------|---------------------------|--------------------------------|---------------------|-------------------------|
| WS-C2960X-48LPS-L | 48 | 4 SFP | LAN Base | 370W | Optional |
| WS-C2960X-24PS-L | 24 | 4 SFP | LAN Base | 370W | Optional |
| WS-C2960X-24PSQ-L | 24 | 2 SFP, 2 10/100/1000BT | LAN Base | 110W | No |
| WS-C2960X-48TS-L | 48 | 4 SFP | LAN Base | - | Optional |
| WS-C2960X-24TS-L | 24 | 4 SFP | LAN Base | - | Optional |
| WS-C2960X-48TS-LL | 48 | 2 SFP | LAN Lite | - | No |
| WS-C2960X-24TS-LL | 24 | 2 SFP | LAN Lite | - | No |

Table 22. Cisco Catalyst 2960-XR Configurations Ordering Information

| Part Number | 10/100/1000 Ethernet Interfaces | Uplink Interfaces | Cisco IOS Software Feature Set | Available PoE Power | Second FRU Power Supply Option | FlexStack-Plus Stacking |
|--------------------|---------------------------------|-------------------|--------------------------------|---------------------|--------------------------------|-------------------------|
| WS-C2960XR-48FPD-I | 48 | 2 SFP+ | IP Lite | 740W | 1025W | Optional |
| WS-C2960XR-48LPD-I | 48 | 2 SFP+ | IP Lite | 370W | 640W | Optional |
| WS-C2960XR-24PD-I | 24 | 2 SFP+ | IP Lite | 370W | 640W | Optional |
| WS-C2960XR-48TD-I | 48 | 2 SFP+ | IP Lite | - | 250W | Optional |
| WS-C2960XR-24TD-I | 24 | 2 SFP+ | IP Lite | - | 250W | Optional |
| WS-C2960XR-48FPS-I | 48 | 4 SFP | IP Lite | 740W | 1025W | Optional |
| WS-C2960XR-48LPS-I | 48 | 4 SFP | IP Lite | 370W | 640W | Optional |
| WS-C2960XR-24PS-I | 24 | 4 SFP | IP Lite | 370W | 640W | Optional |
| WS-C2960XR-48TS-I | 48 | 4 SFP | IP Lite | - | 250W | Optional |
| WS-C2960XR-24TS-I | 24 | 4 SFP | IP Lite | - | 250W | Optional |

Table 23. Cisco Catalyst 2960-X Accessories

| Part Numbers | Description |
|------------------|---|
| C2960X-STACK | FlexStack-Plus hot-swappable stacking module |
| CAB-STK-E-0.5M | FlexStack-Plus stacking cable with a 0.5 m length |
| CAB-STK-E-1M | FlexStack-Plus stacking cable with a 1.0 m length |
| CAB-STK-E-3M | FlexStack-Plus stacking cable with a 3.0 m length |
| CAB-CONSOLE-RJ45 | Console cable 6 feet with RJ45 |
| CAB-CONSOLE-USB | Console cable 6 feet with USB Type A and mini-B connectors |
| PWR-CLP | Power cable restraining clip |
| RCKMNT-1RU-2KX= | Spare rack-mount kit for Cisco Catalyst 2960-X and 2960-XR Series for 19-inch racks |
| RCKMNT-REC-2KX= | 1 RU recessed rack-mount kit for Cisco Catalyst 2960-X and 2960-XR Series |

Table 24. Cisco Catalyst 2960-X Redundant Power Supply Options

| Part Numbers | Description |
|-----------------|---|
| PWR-RPS2300 | Cisco Redundant Power System 2300 and blower, no power supply |
| BLNK-RPS2300= | Spare bay insert for Cisco Redundant Power System 2300 for Cisco Catalyst 2960 and Cisco Catalyst 2960-X switches |
| CAB-RPS2300-E= | Spare RPS2300 cable for Cisco Catalyst 2960-X switches |
| BLWR-RPS2300= | Spare 45 CFM blower for RPS 2300 |
| C3K-PWR-750WAC= | RPS 2300 750W AC power supply spare for Cisco Catalyst 2960-X |

For more information about the RPS-2300, visit cisco.com/en/US/products/ps7130/index.html.

Table 25. Cisco Catalyst 2960-XR Power Supply Options

| Part Numbers | Description |
|-----------------------------------|--|
| PWR-C2-250WAC⁴ | Second FRU power supply and fan for all non-PoE 2960-XR switches, provides 250W AC of power |
| PWR-C2-640WAC⁴ | Second FRU power supply and fan for all 370W PoE+ 2960-XR switches, provides 640W AC of power |
| PWR-C2-1025WAC⁴ | Second FRU power supply and fan for all 740W PoE+ 2960-XR switches, provides 1025W AC of power |
| PWR-C2-250WAC= | Spare FRU power supply and fan for all non-PoE 2960-XR switches, provides 250W AC of power |
| PWR-C2-640WAC= | Spare FRU power supply and fan for all 370W PoE+ 2960-XR switches, provides 640W AC of power |
| PWR-C2-1025WAC= | Spare FRU power supply and fan for all 740W PoE+ 2960-XR switches, provides 1025W AC of power |

Table 26. Cisco Catalyst 2960-X and 2960-XR SFP/SFP+ Modules

| SFP and SFP+ Modules |
|---|
| For the list of supported SFP and SFP+ modules, visit http://www.cisco.com/en/US/products/hw/modules/ps5455/products_device_support_tables_list.html . |

Table 27. Power Cords for Cisco Catalyst 2960-X Product Family

| Part Numbers | Description |
|--------------------------|---|
| CAB-16AWG-AC | AC power cord, 16AWG |
| CAB-ACE | AC power cord (Europe), C13, CEE 7, 1.5M |
| CAB-L620P-C13-US | Power cord, 250VAC, 15A, NEMA L6-20 to C13, US |
| CAB-ACI | AC power cord (Italy), C13, CEI 23-16, 2.5m |
| CAB-ACU | AC power cord (UK), C13, BS 1363, 2.5m |
| CAB-ACA | AC power cord (China/Australia), C13, AS 3112, 2.5m |
| CAB-ACS | AC power cord (Switzerland), C13, IEC 60884-1, 2.5m |
| CAB-ACR | AC power cord (Argentina), C13, EL 219 (IRAM 2073), 2.5m |
| CAB-ACC | CORD, PWR, CHINA, 10A, IEC 320, C13 (APN=CS-PWR-CH) |
| CAB-JPN-12A | CABASY, POWER CORD, JAPAN 2P, PSE, 12A @125VAC |
| CAB-L620P-C13-JPN | Power cord, 250VAC, 15A, NEMA L6-20 to C13, JAPAN |
| CAB-IND | Power cable for India |
| CAB-C15-ISR | Power cable for Israel |
| CAB-ACSA | Power cable for South Africa |
| CAB-AC15A-90L-US | 15A AC power cord, left angle (United States) |
| CAB-ACE-RA | Power cord Europe, right angle |
| CAB-ACI-RA | Power cord Italian, right angle |
| CAB-ACU-RA | Power cord UK, right angle |
| CAB-ACC-RA | Power cord China, right angle |
| CAB-ACA-RA | Power cord, Australian, right angle |
| CAB-ACS-RA | Power cord for Switzerland, right angle |
| CAB-ACR-RA | Power cord, Argentina, right angle |
| CAB-JPN-RA | Power cord, Japan, right angle |
| CAB-C15-CBN | Cabinet jumper power cord, 250 VAC 13A, C14-C15 connectors |
| CAB-ACBZ-12A | AC power cord (Brazil) 12A/125V BR-3-20 plug for less than 12A device |

⁴ The first FRU power supply and fan module is configured automatically when the switch is ordered. The second redundant FRU power supply and fan module is an option while configuring the order.

Table 28. Power Cords for Cisco Catalyst 2960-XR Product Family

| Part Numbers | Description |
|--------------------------|--|
| CAB-3KX-AC | AC Power Cord for Catalyst 2960-XR (North America) |
| CAB-3KX-AC-AP | AC Power Cord for Catalyst 2960-XR (Australia) |
| CAB-3KX-AC-AR | AC Power Cord for Catalyst 2960-XR (Argentina) |
| CAB-3KX-AC-SW | AC Power Cord for Catalyst 2960-XR (Switzerland) |
| CAB-3KX-AC-UK | AC Power Cord for Catalyst 2960-XR (United Kingdom) |
| CAB-3KX-AC-JP | AC Power Cord for Catalyst 2960-XR (Japan) |
| CAB-3KX-AC-EU | AC Power Cord for Catalyst 2960-XR (Europe) |
| CAB-3KX-AC-IT | AC Power Cord for Catalyst 2960-XR (Italy) |
| CAB-3KX-AC-IN | AC Power Cord for Catalyst 2960-XR (India) |
| CAB-3KX-AC-CN | AC Power Cord for Catalyst 2960-XR (China) |
| CAB-3KX-AC-DN | AC Power Cord for Catalyst 2960-XR (Denmark) |
| CAB-3KX-AC-IS | AC Power Cord for Catalyst 2960-XR (Israel) |
| CAB-3KX-250VAC-JP | Japan 250V AC Power Cord |
| CAB-C15-CBN | Cabinet Jumper Power Cord, 250 VAC 13A, C14-C15 Connectors |
| CAB-ACBZ-10A | AC Power Cord (Brazil) 10A/250V BR-3-10 plug for <10A device |
| CAB-ACBZ-12A | AC Power Cord (Brazil) 12A/125V BR-3-20 plug for <12A device |

Contact Cisco

For more information about Cisco products, contact:

- Phone: +1 800 553-NETS (6387)
- [Worldwide Product Support](#)
- Company Website: cisco.com



Americas Headquarters
Cisco Systems, Inc.
San Jose, CA

Asia Pacific Headquarters
Cisco Systems (USA) Pte. Ltd.
Singapore

Europe Headquarters
Cisco Systems International BV Amsterdam,
The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)